

# *R. C. Tronics Incorporated*

**2573 East Kercher Road  
Goshen, Indiana 46528  
Toll Free 1-866-457-7790**

**DAT-01348-13010**  
**08 Conductor Data Cable**  
**Phone 1-574-642-3857**  
**Fax 1-574-642-3858**  
**<http://www.rctronics.com>**

**Viewed with Tyco Connector Plug-In Face Down.**



**Connects to PCB-00745/J1 from PCB-00747.**  
**Operates; "Compartment Open Light, Door Open Light and Battery Light."**

**Carol C-2465, 22 AWG, Stranded 7/30/8, unshielded eight conductor cable.**  
**Cut each jacket end 4 inches long, remove jacket on each end.**  
**Place connector into insertion equipment, start with #8 and complete with #1**  
**Requires one (1) Tyco/Amp. 643813-8 connector & Tyco/Amp. 643075-8 end cap.**

**Terminate right end as shown.**

**Requires one (1) Tyco/Amp 643813-4 & Tyco/Amp. 643075-4 end cap.**  
**Terminate left end as shown.**

## **CHECK CABLE WITH CABLE CHECKER**

**#1 BLACK, #2 RED, #3 GREEN, #4 BROWN,**

**#5 BLUE, #6, ORANGE, #7 YELLOW, #8 WHITE**

D  
A  
T  
  
0  
0  
0  
0  
0  
  
0  
0  
  
0  
0  
  
0  
0

1st three Letters = Data Cable

2nd five numbers = Print Number

3rd two numbers = Configuration

4th two numbers = Length In Feet

5th last digit = Length In Inches