

R. C. Tronics Incorporated

2573 East Kercher Road
Goshen, Indiana 46528
Toll Free 1-866-457-7790

Phone 1-574-642-3857
Fax 1-574-642-3858
<http://www.rctronics.com>

DAT-01347-03XXX 4 Conductor Data Cable

Viewed with Tyco Connector Plug-In Face Down.



Cable for RCT-01755, Ambulance Type 2 to RCT-00772 Body Flasher.

Carol C0742, 22 awg. Standard unshielded four conductor.

Cut both end jackets, 4 inches long and remove from each end.

Requires one Tyco / Amp connector 643814-4 and 643075 strain relief.

Requires one Tyco / Amp connector 643814-3 and 643075 strain relief.

Terminate all conductors beginning with 3 or 4 and ending with 1.

#1 BLACK = BATTERY NEGATIVE, "SECONDARY".

#2 WHITE = BATTERY NEGATIVE, "PRIMARY".

#3 RED = BATTERY POSITIVE "SECONDARY".

#4 GREEN = BATTERY POSITIVE, "PRIMARY".

D
A
T

0
0
0
0
0

0
0

0
0

0
5th last digit = Length In Inches

1st three Letters = Data Cable

2nd five numbers = Print Number

3rd two numbers = Configuration

4th two numbers = Length In Feet