R. C. Tronics Incorporated

2573 East Kercher Road Goshen. Indiana 46528 Toll Free 1-866-457-7790

DAT-01348-21XXX

Phone 1-574-642-3857 Fax 1-574-642-3858 08 Conductor Data Cable http://www.rctronics.com

Viewed with Tyco Connector Plug-In Face Down.



Carol C-2465, 22 AWG, Stranded 7/30/8, unshielded eight conductor cable. Cut each jacket end 4 inches long, remove jacket on each end. Add heatshrink with DAT part number.

Requires two (2) Tyco/Amp. 643814-8 connector & Tyco/Amp. 643075-8 end cap. Place connector into insertion equipment, start with #8 and complete with #1

CHECK CABLE WITH CABLE CHECKER

#1 BLACK, #2 GREEN, #3 BROWN, #4 BLUE,

#5 ORANGE, #6, YELLOW, #7 WHITE #8 LEAVE OPEN

D A T	1st three Letters = Data Cable
0 0 0 0	2nd five numbers = Print Number
0	3rd two numbers = Configuration
0	4th two numbers = Length In Feet
0	5th last digit = Length In Inches